

# Motorola Semiconductor Engineering Bulletin

---

## EB277

## Coherency in the Time Processor Unit (TPU)

By Sharon Darley  
Austin, Texas

### General Information

---

Sometimes, two parameters in the time processor unit (TPU) parameter RAM must be updated together. In other words, if one parameter is updated, the other also must be immediately updated. This is called coherency.

A data transfer is coherent if all of the data is transferred before any of it is updated or used. Thus, all of the data must be read or written at the same time. Some of the current TPU functions have two parameters that need to be read or written coherently.

An example is the PWM function. Its parameters, PWMHI (the pulse high time) and PWMPER (the pulse period), must be written coherently or else the TPU may use one parameter before the other is updated, thus generating an incorrect waveform.


Another example is the ITC function. Its parameters MAX\_COUNT (the maximum number of transitions to be counted) and TRANS\_COUNT (the current count) must be accessed coherently; otherwise, the TPU may update TRANS\_COUNT between the two accesses.

The only way to coherently access two parameters in the parameter RAM is to do a long-word read or write. Doing two back-to-back word writes will not guarantee coherent access. The control registers cannot



be guaranteed coherent access. For them, doing a long-word read or write is no different than doing two back-to-back word writes.

Although all of the parameter RAM and control registers are word accessible, the channel interrupt status register (CISR) is the only register that is byte accessible. If a byte is written to any other parameter RAM location or control register, the TPU will correctly write to the byte selected, but will write all 1s to the other half of the parameter RAM location.

Motorola reserves the right to make changes without further notice to any products herein. Motorola makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Motorola assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation consequential or incidental damages. "Typical" parameters which may be provided in Motorola data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. Motorola does not convey any license under its patent rights nor the rights of others. Motorola products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the Motorola product could create a situation where personal injury or death may occur. Should Buyer purchase or use Motorola products for any such unintended or unauthorized application, Buyer shall indemnify and hold Motorola and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that Motorola was negligent regarding the design or manufacture of the part. Motorola and  are registered trademarks of Motorola, Inc. Motorola, Inc. is an Equal Opportunity/Affirmative Action Employer.

#### How to reach us:

**USA/EUROPE/Locations Not Listed:** Motorola Literature Distribution, P.O. Box 5405, Denver, Colorado 80217, 1-800-441-2447 or 1-303-675-2140. Customer Focus Center, 1-800-521-6274

**JAPAN:** Nippon Motorola Ltd.: SPD, Strategic Planning Office, 141, 4-32-1 Nishi-Gotanda, Shinagawa-ku, Tokyo, Japan. 03-5487-8488

**ASIA/PACIFIC:** Motorola Semiconductors H.K. Ltd., 8B Tai Ping Industrial Park, 51 Ting Kok Road, Tai Po, N.T., Hong Kong. 852-26629298

**Mfax™, Motorola Fax Back System:** RMFAX0@email.sps.mot.com; <http://sps.motorola.com/mfax/>;

TOUCHTONE, 1-602-244-6609; US and Canada ONLY, 1-800-774-1848

**HOME PAGE:** <http://motorola.com/sps/>

Mfax is a trademark of Motorola, Inc.



**MOTOROLA**

© Motorola, Inc., 1998

EB277/D